

3. Accessing User Tools

User Tools Settings

When the IPDS card is installed, IPDS print settings become available and will appear on the control panel.

❖ List / Test Print

- IPDS Font List
Prints a list of IPDS-supported fonts.

Note

- IPDS Font List is printed on A4  or 8 1/2" × 11"  size paper, so load them into Tray 1.
- For details about printing lists, see the manual explaining how to print lists provided by the supplier.

❖ Maintenance

- Reset IPDS Fonts
Use this page to delete all IPDS captured fonts.

Note

- Only the Machine Administrator can reset IPDS fonts.

❖ IPDS Menu

Menu Item	Description
Tray Form	Specify an IPDS form for each paper tray. For each paper tray, select the form you want to allocate to it.
Emulation Mode	Specifies the emulation mode. <ul style="list-style-type: none">• Native (Default)• 4028
Print Mode	Specifies the print mode. <ul style="list-style-type: none">• Standard• Enhanced (Default)
Default Code Page	Specifies the default code page. The default value is "037". 037 US, Canada, Netherlands, Portugal 038 US English ASCII 260 Canadian French 273 Austrian/German 274 Belgium 276 Canadian French

Menu Item	Description
Default Code Page	277 Danish/Norwegian 278 Finnish/Swedish 280 Italian 281 Japanese 284 Spanish 285 UK English 286 Austrian/German (alternate) 287 Danish/Norwegian (alternate) 288 Finnish/Swedish (alternate) 290 Japanese/Katakana 297 French 420 Arabic 423 Greek 424 Hebrew 500 Belgium, Switzerland / International 870 Latin 2 Multilingual 871 Icelandic 875 Greek 880 Cyrillic 892 OCR - A 893 OCR - B 905 Turkish 1025 Cyrillic 1026 Turkish The following code pages include the Euro character: <ul style="list-style-type: none"> • 1140 - US, Canada, Netherlands, Brazil, Portugal • 1141 - Austrian/German • 1142 - Danish/Norwegian • 1143 - Finnish/Swedish • 1144 - Italian • 1145 - Spanish • 1146 - UK English • 1147 - French • 1148 - Belgium, Switzerland/International • 1149 - Icelandic

Menu Item	Description
Default FGID	<p>Specifies the default FGID (Font Typeface Global Identifier), which identifies the printer's default resident font. The default FGID is 416 (Courier 10 point).</p> <p>To display a list of the fonts and FGIDs that the printer supports, print out the list of IPDS resident fonts. For details about printing lists, see the manual explaining how to print lists provided by the supplier.</p> <p>3 OCR B</p> <p>11 Courier 10</p> <p>12 Prestige Pica</p> <p>18 Courier Italic 10</p> <p>19 OCR A</p> <p>46 Courier Bold 10</p> <p>85 Courier 12</p> <p>86 Prestige Elite</p> <p>92 Courier Italic 12</p> <p>111 Prestige Elite Bold</p> <p>112 Prestige Elite Italic</p> <p>159 Boldface</p> <p>164 Prestige PSM Roman Medium</p> <p>203 Gothic Text</p> <p>221 Prestige 15</p> <p>223 Courier 15</p> <p>254 Courier.17 ss</p> <p>256 Prestige 17</p> <p>281 Letter Gothic</p> <p>283 Gothic Text</p> <p>290 Gothic Text</p> <p>304 Katakana Gothic</p> <p>305 OCR A</p> <p>306 OCR B</p> <p>318 Prestige Bold</p> <p>319 Prestige Italic</p> <p>400 Letter Gothic</p> <p>404 Letter Gothic Bold</p> <p>416 Courier Roman Medium 10</p> <p>420 Courier Roman Bold</p>

Menu Item	Description
Default FGID	424 Courier Italic Medium 428 Courier Italic Bold 432 Prestige 2304 Helvetica Roman Medium 2305 Helvetica Roman Bold 2306 Helvetica Italic Medium 2307 Helvetica Italic Bold 2308 Times New Roman Medium 2309 Times New Roman Bold 2310 Times New Roman Italic Medium 2311 Times New Roman Italic Bold 5687 Times Roman 5707 Times Roman Bold 5815 Times Roman Italic 5835 Times Roman Bold Italic 20224 Boldface
Characters Per Inch	Specifies the number of characters per inch (pitch) for the default font. Valid values are 5.0 to 30.0 in units of one tenth of an inch. The default value is 10.0.
Valid Printable Area Check	Turns valid printable area checking on or off. <ul style="list-style-type: none"> • On (Default) The printer checks for pixels that fall outside the intersection of the logical and physical pages. If there are pixels outside the area and error reporting has been set using the "IPDS Exception Handling Control" command, the printer reports an error to the host. • Off The printer does not report pixels outside the valid printable area.
Page	Specifies how data is positioned on the page. <ul style="list-style-type: none"> • Whole (Default) IPDS whole page. The printer does not move or compress the page. This is the preferred method; all page positioning and formatting is done at the application level on the host. The [Print], [Comp1], and [Comp2] commands may alter the appearance of the page, or may not be compatible with earlier products (for example, 3116, 3916), especially if these options are used in combination with duplex and other IPDS Menu page format adjustments. The [Print], [Comp1], and [Comp2] commands are included to allow line printer jobs to fit onto pages where "Edge to Edge" printing is not possible; we do not recommend you use them to create new applications.

Menu Item	Description
Page	<ul style="list-style-type: none"> • Comp1 This command uses the “Print Page” command as its base, and compresses the spacing between text lines generated by the “IPDS Begin Line” command. Its primary purpose is to compress “Begin Line” command text data onto pages that have unprintable borders. • Comp2 This command uses the “Print Page” command as its base, and compresses “IPDS Begin Line” command text (see Comp1) and the data of the following vertical text positioning commands: “Absolute Move Baseline”, “Relative Move Baseline”, “Draw B Axis Rule”, and “Draw I Axis Rule”. <p> Note</p> <ul style="list-style-type: none"> <input type="checkbox"/> Alignment problems can occur if you select [Comp1] or [Comp2], and print jobs that mix text with images, graphics, or bar codes. Problems can occur if text positioning commands are used to move across text or into non-text (image, graphic, or bar code) areas. Both [Comp1] and [Comp2] reduce the line spacing of text only and have no effect on non-text data. To minimize alignment problems, select [Comp1], because “Begin Line” commands are not normally used to move across or into non-text areas. If, however, the application you want to compress does not use the “Begin Line” command, select [Comp2]. <ul style="list-style-type: none"> • Print IPDS print page. If the page origin is within the unprintable area, the origin of the page is moved to the inside edge of the nearest unprintable area border. If the origin violates the unprintable area on two edges, it is moved to the nearest inside corner of the unprintable area. If the origin violates only one edge of the unprintable area, the origin is adjusted to avoid that area only. If a location adjustment is made, the printed page is shifted in the direction of the adjustment. There is no compression, so data on the opposite edge may be pushed off the page. <p> Note</p> <ul style="list-style-type: none"> <input type="checkbox"/> For the “Print” command to function, the [Edge to Edge] setting must be set to [Off]. Any data placed in this unprintable area is lost. Also, [Print] will not function on media overlays (overlays that are part of the base page, not the overlays included in the variable print data).
Edge to Edge	<p>Turns “Edge to Edge” printing on or off.</p> <ul style="list-style-type: none"> • Off (Default) The printer maintains a border of 2 mm (0.078 in) on the leading edge, but prints to all other page borders. • On The printer allows printing up to the physical page size.

Menu Item	Description
Edge to Edge	<p> Note</p> <ul style="list-style-type: none"> <input type="checkbox"/> prevent toner accumulating inside the printer, we recommend leaving [Edge to Edge] set to [Off] for IPDS, and setting it to [On] only when necessary. <input type="checkbox"/> The “Edge to Edge” IPDS Menu item affects IPDS data only.
Font Substitution	<p>Turns font substitution on or off.</p> <ul style="list-style-type: none"> • Off (Default) If a job requests a font that is not loaded on the printer, the printer generates an IPDS NACK (Negative Acknowledgement) message and the host holds the job. • On If a job requests a font that is not loaded on the printer, the printer uses a substitute font.
Caching	<p>Specifies whether or not to use caching for repeated overlays.</p> <ul style="list-style-type: none"> • On The printer uses caching, which provides better performance for jobs with repeated overlays, but uses more memory. • Off (Default) The printer does not use caching, which requires less memory but provides less performance for jobs with repeated overlays. <p> Note</p> <ul style="list-style-type: none"> <input type="checkbox"/> Overlay caching is recommended for repeated overlays. Overlay caching does not improve performance with non-overlay IPDS data or overlays that are used only once or infrequently.
Font Capture	<p>Sets Font Capture processing:</p> <ul style="list-style-type: none"> • On (Default) The printer saves downloaded font resources on its hard disk drive for use beyond the duration of the current power cycle. The IPDS host must provide the “Activate Resource” command with the correct resource identifiers before downloading the font resource to be captured. • Off The printer stores downloaded font resources for the duration of one power cycle only.
Resolution	<p>Specifies the resolution reported to the host in the “IPDS XOA-OPC” command for raster coded fonts and IM1 image support. The [Resolution] menu item also helps determine whether or not a printer-resident raster font is used. For example, 240 dpi raster fonts are activated at the [240 dpi] setting, not at [300 dpi] or [600 dpi]. The [Resolution] setting does not affect outline fonts, nor does it determine which raster fonts can be downloaded to the printer as temporary activation fonts.</p>

Menu Item	Description
Resolution	<ul style="list-style-type: none"> • 300 dpi (Default) Reports to the host that the printer supports 300 dpi raster fonts and IM1 images. “Resident” or “Captured” raster fonts of other resolutions are not activated unless a matching “Font Resolution” and “Metric Technology Triplet” is provided with the activation request. • 600 dpi Reports to the host that the printer supports 600 dpi raster fonts and IM1 images. “Resident” or “Captured” raster fonts of other resolutions are not activated unless a matching “Font Resolution” and “Metric Technology Triplet” is provided with the activation request. • 240 dpi Reports to the host that the printer supports 240 dpi raster fonts and IM1 images. “Resident” or “Captured” raster fonts of other resolutions are not activated unless a matching “Font Resolution” and “Metric Technology Triplet” is provided with the activation request. • Auto Reports to the host that the printer supports raster fonts of any dpi value and IM1 images. “Resident” or “Captured” raster fonts of other resolutions are not activated unless a matching “Font Resolution” and “Metric Technology Triplet” is provided with the activation request. <p> Note</p> <ul style="list-style-type: none"> <input type="checkbox"/> If you select [Standard] for the [Print Mode] setting, the resolution changes to [300 dpi]. <input type="checkbox"/> To set the IPDS resolution to [240 dpi], [600 dpi], or [Auto], you must first set [Print Mode] to [Enhanced]. Enhanced print mode produces optimal print quality; but can slow down the printing of complex jobs.
Graphic Character String	<p>Specifies the Graphic Character String (Graphic Character Sizing) processing method.</p> <ul style="list-style-type: none"> • Auto (Default) Applies the value specified by the [Emulation Mode] item ([Native] or [4028]). • Character Scale Applies 4028 IPDS Emulation. Prints graphics and text characters by scaling the characters in a currently activated font. Character cell size is defined in the GOCA data stream. Not available for DBCS. • Font Activation Applies Native IPDS Emulation. Prints graphics and text characters using a currently activated font at the font’s activation size, without scaling. GOCA data stream Character cell size information is ignored.

Menu Item	Description
Bar Code	<p>Specifies the barcode level protocol.</p> <ul style="list-style-type: none"> • Auto (Default) Applies the value specified by the [Emulation Mode] item ([Native] or [4028]). • 4028 Applies 4028 IPDS Emulation. • Native Applies Native IPDS Emulation.
Box Draw	<p>Specifies the Box Draw processing.</p> <ul style="list-style-type: none"> • Off (Default) Uses Symbol Set outline font characters to draw boxes as the font-defined characters. • On Uses special outline fonts to draw Symbol Set box characters. Select [On] to fill gaps caused by special raster fonts that contain extended length box characters (as found in older applications, for example).
Color Simulation	<p>Allows you to select how color specification controls are processed on a monochromatic printer.</p> <ul style="list-style-type: none"> • Fidelity (Default) The printer accepts all color specification controls and simulates unique colors with shades of gray. • Legacy The printer accepts all color specification controls; but performs only limited color simulation using black.
Text Color Simulation	<p>Specifies how text color specification controls are processed on a monochrome laser printer.</p> <ul style="list-style-type: none"> • On (Default) The printer accepts all text color specification controls and simulates the unique colors with shades of gray. • Off The printer accepts all text color specification controls; but performs only limited color simulation using black. <p> Note</p> <p><input type="checkbox"/> This menu item is available only if [Color Simulation] mode is set to [Fidelity].</p>
Suppress Staple Count Nacks	<p>Select whether or not to notify the user when stapling errors occur.</p> <ul style="list-style-type: none"> • On • Off (Default)
Suppress Punch Nacks	<p>Select whether or not to notify the user when punching errors occur.</p> <ul style="list-style-type: none"> • On • Off (Default)

Menu Item	Description
Tray Parameter	Maps the media source (input tray) to an ID the host uses for the media source. <ul style="list-style-type: none"> • Auto (Default) • IPDS Tray If [IPDS Tray] is selected, enter the tray parameter replacement value for each paper tray, using up to 254 digits.
Corner Staple Angle	Select [Vertical] or [Slant] for the angle of stapling. <ul style="list-style-type: none"> • Vertical (Default) Staples vertically. • Slant Staples diagonally.
Offset	Specifies whether or not the output is offset (jogged). <ul style="list-style-type: none"> • On (Default) Output is offset (jogged) when requested by the job. • Off Output is never offset (jogged).
Default Punch Pattern	Specifies the default number of holes to punch if the punch unit provides a selection (for example, two or four holes).

 **Note**

- [Suppress Staple Count Nacks]** and **[Corner Staple Angle]** appears if the optional staple unit is installed.
- [Suppress Staple Count Nacks]** and **[Default Punch Pattern]** appears if the optional punch unit is installed.
- [Tray Form]** and **[Tray Parameter]** appear differently depending on the options installed.
- [Tray Form]** allocates the form specified using Web Image Monitor's **[IPDS Form Settings]** to the installed tray. For details about IPDS Form Settings, see the Web Image Monitor Help.
- Tray commands of **[Tray Form]** differ depending on the machine you want to use. For details about selectable tray commands, see "Load Copy Control", IPDS Technical Reference.
- For details about the control panel settings, see the manual explaining how to specify the control panel settings, provided by the supplier.

